


# **EAGLES INTERNATIONAL**

**A CHAPTER OF  
FAMILY MOTOR COACH ASSOCIATION  
NEWSLETTER SUMMER OF 2020**



**President – Marty Golden**  
**Eastern VP – Eric Brown**  
**Central VP – Mel Legg**  
**Southwest VP – Randy Coons**  
**Northwest VP – Daniel Bowers**

**Secretary – Sandy Gilbert**  
**Treasurer – Denise Hufford**  
**National Director – Wayne Schell**  
**Alternate National Director – Jim Hufford**

**Newsletter Editor – Marty Golden**  
**432-638-9015 | goldenspecialties@gmail.com**  
**5101 East County Rd 120 | Midland, TX 79706**

**Jim Shepherd – Network Administrator**  
**[www.eaglesinternational.net](http://www.eaglesinternational.net)**

## **PRESIDENT'S MESSAGE**

Greetings Eagles International members: Quite a bit has happened since our last newsletter. I hope you and yours have made it through OK. There are a couple of things going on I'd like to bring up.

First, our last newsletter had a roster of all our members. Included were phone number, address, and email. As crazy as things have been feel free to reach out to other members and just say hey or ask about their bus. Some people may like to get a call.

Next, we have two rallies coming up. One in Kansas, and one in Branson. From what I hear folks are ready to play, so I'm looking for a good turn out. Mike and Susan Groves are putting on a rally at Crawford State Park in Kansas on Oct. 3-6 then whoever wants to can convoy over to Branson where Byron and Betty Pigg will host a rally Oct. 7-10. At the Branson rally we will have our annual business meeting, and also Wayne St. Onge has donated quite a few Eagle parts to be auctioned off. So practice raising your arm. We could not have the Iowa rally this year.

Next, I am including two things that you might like. One is an article by Jim Shepherd on using relays to wire for towing. I put these on everything that has a separate brake light wire (not with blinkers), and it works very well. Then there is a weight scale kit that I found on the computer. I built one of these and I can weigh each wheel on the bus or things that you ship.

Finally, all members are also members of FMCA. I would like to give a shout out to them. They have some good benefits and they also do a bunch of stuff behind the scenes that we don't see, such as lobbying on our behalf so that some of the rules that apply to commercial vehicles do not apply to RV's.

I would also like to thank Jim Shepherd and James Polsfuss for all they do with the website. They put in a lot of hours so we can have a first class site.

Safe travels, Marty Golden, F299092

# Trailer/Toad Wiring Conversion System

## Using Standard Relays

By Jim Shepherd, RV Safety Systems

Most buses have separate brake and turn lights, while virtually all towed vehicles and trailers have combined brake and turn lights. This condition requires some sort of conversion system that is commonly called a 5 to 4 wire converter. Fig. 1 shows a commercial unit where five wires from the bus are connected to one side of the converter and 4 wires from the converter are connected to the trailer connector.

The five wires from the bus are:

1. Ground
2. Tail Light
3. Left Turn
4. Right Turn
5. Brake

The wires exiting the converter are:

1. Ground
2. Tail Light
3. Left Turn/Brake
4. Right Turn/Brake

My experience with commercially made converters is that they are not very reliable. I have just experienced my second failed unit in less than three years and 50K miles. They are not expensive, but it is still a pain to find

one and replace it when you are on the road.

There are other issues when wiring a bus for towing. First is the fact that buses




Figure 1: Commercial 5 wire to 4 wire converter.

were not designed for towing and the wiring might have marginal current capacity to handle the additional trailer/toad lights. Second, some buses are 24-volt and conversion to 12-volts must be accomplished. A properly designed relay conversion system address both issues.

On the Bus Conversion Bulletin Board, there have been several threads discussing the 5 to 4 wire conversion issues. I recalled that some folks had accomplished the conversion with standard relays. Relays are used extensively in our buses for a large number of applications. They are very reliable and relatively easy to obtain. The converter system made with these relays is easy to repair – simply replace one of the relays.

In my fire suppression system, I use the same Bosch-

type automotive relay that is used in Eagle buses (perhaps others) and many over-the-road trucks. I decided to design my system around these relays. My electronic skills are a bit limited, so I searched for ideas after spending a few hours designing the system only to find that it did not function properly for all conditions. The first site I went to was: [http://www.gumpydog.com/bus/MC9\\_WIP/Electrical/Tail\\_Light\\_Converter/tail\\_light\\_converter.htm](http://www.gumpydog.com/bus/MC9_WIP/Electrical/Tail_Light_Converter/tail_light_converter.htm). Craig Shepard has documented a system that does the 5 to 4 conversion and the 24-volt to 12-volt conversion using MCI relays. Fig. 2 is Craig's wiring diagram. Craig has built some of these systems for other bus folks who did not feel comfortable building their own. If you would like to contact Craig, his email address is [craig@gumpydog.com](mailto:craig@gumpydog.com). As a side note, Craig's bus project pages contain a huge amount of great ideas for the conversion process.

I worked my way through Craig's schematic and built my own using four Bosch-type relays and the system works very well. Fig. 3 is a wiring diagram furnished by Sean Welsh. Many of you know Sean from the Bus Conversion board, since he is the resident electrical expert who has bailed many of us out. I found Sean's diagram after I spent hours making a complex drawing for my system. His is very straight forward and much easier to visualize. Again, as a side note, Sean and Louise publish a fabulous blog about full-timing life on the road in their very unique Neoplan bus (<http://ourodysey.blogspot.com/>)

Before we talk about the relay based converter system, let's talk about the Bosch-type automotive-type relay. It is a standard relay used extensively in the bus and heavy truck market. Several manufacturers make this relay and most rate them for a one million mechanical cycle life, minimum. The relay is typically described as an ISO standard automotive relay. They are very




Figure 2

inexpensive and readily available. These relays come in many versions including weatherproof, with diodes across the coil, with/without mounting tabs, etc. Some sources are:

**Digi-Key (www.digikey.com)**

Tyco, part number PB682-ND (12V with diode)

Tyco, part number PB684-ND (24V with diode)

**Del City (www.delcity.net)**

73986 (12V with diode)

73570 wired socket only


be overloaded. The bus wires will only be used to trigger the relays (negligible current) and the power for the trailer/toad lights will be supplied by a auxiliary 12-volt source.

For a 24V bus, the wiring will be the same as the 4-relay, 12-volt system, but 24-volt relays will be used. The 24-volt signals will trigger the relays, which will then connect the 12-volt power source to the proper output terminal.

Both Sean and Craig suggest that each trailer/toad circuit have a circuit breaker

wired into the system. That is not the norm for most trailer wiring, but it would offer maximum protection.

The best way to connect the relay system components is to use either a screw or stud terminal block (see Fig. 4). The number of connections will require a 12 terminal connection block. Del City part numbers for these are 70022 (screw type) or 70005 (stud type). Using these blocks will provide a clean installation and allow easy troubleshooting.




**Figure 3: Trailer converter wiring schematic using Bosch-type automotive relays**

I have listed relays that have built-in diodes connected to the coil terminals. The diodes prevent voltage spikes when the relay coil is de-energized. For this application, that would probably not be an issue, but the added cost is negligible. Relays with diodes are polarity sensitive. The coil connections must be wired so that terminal 85 is the ground terminal and terminal 86 is the signal. These relays are not weatherproof, so they should be mounted in an enclosure or an area not subjected to significant amounts of fluids. The relays are less than \$5.

In addition to the relays, I listed a wired socket that makes wiring the relays very simple. It is possible to connect the wires to the relays using female spade connectors, but that makes replacing the relay a bit tedious and can result in loose connections. The sockets are less than \$2.

A bus with a 12V system could be designed with three relays. However, I recommend that a four-relay system be utilized. One relay will be activated by the brake signal, one activated by the right turn signal, one activated by the left turn signal and the fourth relay will be activated by the tail light signal. The ground will be connected directly to the trailer connector. Using a four-relay system will assure that the bus wiring will not



**Figure 4: Shepherd installation**

*I would like to acknowledge the assistance and guidance that Sean Welsh and Craig Shepard offered for this article.*

# Floor Scale Kits from \$395

[ [Home](#) ] [ [Floor scale kit installed](#) ]

**A and A Scales LLC**

Phone 800-481-4114 or 973-800-3965

Open 7 days a week

No sales tax for customers outside New Jersey



**We will not be undersold!**



E-MAIL

## FSK Floor Scale kit from \$395 free shipping

Build your own scale at a fraction of the price



[Click here for Dimensional Drawing of Tank Mount](#)

### Floor Scale Kit


Includes mounting blocks, load cells, weight indicator, feet, junction box & hardware

### Tank Mount Kit

Includes Mounts, Load Cells, weight indicator, Junction box & hardware



Weight Indicator included with the kit



Close up of load cell mounted under a platform  
**FSK Scale kit from \$395**

**Free shipping in the continental U.S. for the scale kits**  
[For complete floor scales click here](#)

**Includes the following:**

- One Digital weight indicator with quick disconnect and RS232 printer/computer output, choice of 110V Electric or Battery powered (AA batteries)
- Weighs in Lbs and Kgs
- Four nickel plated steel load cells (stainless steel optional)
- Four Alloy steel load cell feet or (Tank Mount kit does not use feet)
- Four tool steel mounting plates with hardware
- Nema 4X stainless steel junction box
- 15 ft of load cell cable

Build your own floor scale for a fraction of the cost. The weight indicator has five front panel keys: LB/KG, TARE, ZERO, PRINT & NET/GROSS. Drawings and Technical support provided at no extra charge. **Do not weld** with the load cells installed.

The platform can be almost any size as long as it does not flex in the middle

[Click here for photos of a floor scale made by a customer](#)

Load Cell Capacity	Floor Scale Kit	Tank Scale Kit
(4) 250 lb load cells with kit	\$645	\$1495
(4) 500 LB load cells with kit	\$645	\$1495
(4) 1000 lb load cells with kit	\$645	\$1495
(4) 2,000 LB load cells with kit	\$645	\$1495
(4) 2,500 LB load cells with kit (10,000 lb total)	\$395 <b>Buy ▶</b> Free Shipping	\$1495
(4) 5,000 LB load cells with kit (20,000 lb total)	\$395 <b>Buy ▶</b> Free Shipping	\$1495
(4) 10,000 LB load cells with kit	\$995	\$1995
<b>Options</b>	The kit already includes a weight indicator. The WPI-600 is in case you wish to upgrade to a stainless steel display	
WPI-600 stainless steel indicator (battery & Electric powered)	add \$200	add \$200

Entrance to the Crawford State Lake is marked by this tribute to the Civilian Conservation Corps, which built the lake in the late 1940s.



# Kansas Eagle Bus Rally

Oct. 3-6

## Crawford State Park

Farlington, Kansas • [www.KDWPT.crawfordsp@ks.gov](http://www.KDWPT.crawfordsp@ks.gov)

Hosted by Mike and Susan Groves.

Join us for 4 days of fun and interesting activities.

Make your own reservation for campsites in Oak Point

Call 620-362-3671

Sites 145-162 will be held until May 1.

Mike and Susan are site 152 across from a shelter toadstool.

Single pads \$21 and double pads \$37 (split the cost with an Eagle friend).

There are 4 double pads. There is \$5 fee for your car/truck.

Since you pay for your own campsite, the rally fee is \$40.

Send to Mike Groves

902 W. Main, Cleveland, MO 64734

Name(s) \_\_\_\_\_

Address \_\_\_\_\_

City \_\_\_\_\_ State \_\_\_\_\_ Zip \_\_\_\_\_


Phone \_\_\_\_\_ Email: \_\_\_\_\_

We will send you a Crawford State Park brochure with a map, etc.

Mike's cell - 573-220-0243 and Susan's cell 573-220-9153.

On Oct 7, we'll caravan down to Branson!!

FYI sourdough pancakes will happen in Branson!



## BRANSON 4 DAY EAGLE RALLY

BRANSON LAKE SIDE RV PARK, LAKE TANEYCOMO  
NEXT TO BRANSON LANDING, BRANSON MO.  
OCT 7 THRU OCT 10, 2020

BRANSON LANDING ACTIVITIES-WATER SHOW EVERY NIGHT  
ONE MILE OF SHOPS INCLUDING BELKS, BASS PRO, RESTAURANTS,  
ALL SHOPS WITHIN WALKING DISTANCE

BRANSON LAKESIDE RV PARK  
300 S. BOX CAR WILLIE DRIVE  
BRANSON MISSOURI 65616

RALLY FEE \$170 for two people  
one coach, includes full hookup  
4 nights for first 27 coaches

Note: if you want to stay longer contact the campground: [www.cityofbranson.org](http://www.cityofbranson.org)

TRAIL BOSS BYRON PIGG: home phone 417-753-2285; cell 417-840-9343  
E-Mail: [85eagle15@gmail.com](mailto:85eagle15@gmail.com)

Please make checks payable and mail to  
Byron Pigg, 875 Pedelo Rd, Rogersville MO 65742  
Registration deadline Aug 30, 2020

---

Name(s) \_\_\_\_\_ Phone \_\_\_\_\_

Address \_\_\_\_\_ E-Mail \_\_\_\_\_

City \_\_\_\_\_ State \_\_\_\_\_ Zip \_\_\_\_\_

Bill Pratt  
4211 Gentry Lane  
Carson City, NV 89701